

## 数据转换器

D/A转换器

P.24

A/D转换器

P.24

## D/A转换器

## 8bit

## 标准8bit分辨率

用8bit精度(256级)可控制输出电压。这是更普及的类型，功能也非常丰富。

Part No.	Supply Voltage (V)	ch	Current Consumption (mA)	DNL (LSB)	INL (LSB)	Load Current (mA)	Data Transfer Clock Frequency (MHz)	Input type	Data Latch Method	Package
BH2219FVM	2.7 to 5.5	2	0.4	±1.0	±1.5	±1.0	10	CMOS	LD	MSOP8
BH2227FV	2.7 to 5.5	4	0.8	±1.0	±1.5	±1.0	10	CMOS	CSB	SSOP-B14
BH2228FV	2.7 to 5.5	6	0.8	±1.0	±1.5	±1.0	10	CMOS	CSB	SSOP-B14
BH2226FV	2.7 to 5.5	8	1.1	±1.0	±1.5	±1.0	10	CMOS	CSB	SSOP-B16
BH2223FV	2.7 to 5.5	10	1.6	±1.0	±1.5	±1.0	10	CMOS	LD	SSOP-B16
BH2221FV	2.7 to 5.5	12	1.6	±1.0	±1.5	±1.0	10	CMOS	LD	SSOP-B20

## 10bit

## 10bit分辨率

Part No.	Supply Voltage (V)	ch	Current Consumption (mA)	DNL (LSB)	INL (LSB)	Load Current (mA)	Data Transfer Clock Frequency (MHz)	Input type	Data Latch Method	Package
BU2508FV	4.5 to 5.5	4	4.5	±1.0	±3.5	±2.0	10	TTL	LD	SSOP-B14
BU2507FV	4.5 to 5.5	6	4.5	±1.0	±3.5	±2.0	10	TTL	LD	SSOP-B14
BU2506FV	4.5 to 5.5	8	4.5	±1.0	±3.5	±2.0	10	TTL	LD	SSOP-B20
BU2505FV	4.5 to 5.5	10	4.5	±1.0	±3.5	±2.0	10	TTL	LD	SSOP-B20
BU22210MUV	2.7 to 5.5	10	1.2	±0.5	±2.0	±1.0	10	TTL	CSB	VQFN016V3030

## A/D转换器

## 高精度12bit A/D转换器(工业设备用)

Part No.	Supply Voltage (V)	ch	Current Consumption (mA)	DNL (LSB)	INL (LSB)	Sampling Rate (MSPS)	I/F	Architecture	Package
BU79100G-LA	2.7 to 5.25	1	1.6	-1.0 to +1.0	-1.1 to +1.0	1.0	SPI	SAR	SSOP6