
General Purpose Chip Resistors < Low ohmic> < High Power> **MCRL** series

Datasheet

Features

- 1) Realized downsizing and high rated power by changing the design of the resistive element.
- 2) Very-low ohmic resistance from 47m Ohm is in line up by thick-film resistive element.
- 3) High reliability chip resistor employing metal glaze as resistive element
- 4) ROHM resistors have obtained ISO9001 / IATF1649 certification.
- 5) Corresponds to AEC-Q200.



Products list

Part No.	Si	ze	Rated power	Rated ambient	Rated terminal	Resistance tolerance	Temperature coefficient	Resistance range	Operating temperature	Automotive grade										
				temperature	temperature				range	Available										
	(mm)	(inch)	(W)	(°C)	(°C)	(%)	(ppm/°C)	(Ω)	(°C)	(AEC-Q200)										
MCR10L	2012	0805	0.50	70	_	F(±1%)	0~250	47m≦R<120m (E24 series)	-55 ∼ +155	Yes										
Morrioz	2012	0000	0.00	70		J(±5%)	0∼150	120m≦R≦910m (E24 series)	00 10 100	100										
MCR18L	3216	1206	0.75	70	_	F(±1%)	0~250	47m≦R<100m (E24 series)	-55 ∼ +155	Yes										
MORTOL	3210	1200	0.73	70		J (±5%)	0~150	100m ≦R ≦910m (E24 series)	-55 /0 1155	163										
							0~150	47m ≦R < 100m (E24 series)												
<i>New</i> MCR25L	3225	1210	1.25	1.25 70 1:	125	125	125	125	125	125	125	125	125	D (±0.5%) F (±1%)	0~125	100m ≤R < 220m (E24 series)	-55 ∼ +155	Yes		
WCR25L	3223	1210	1.25	70										123	125	123	123	123	123	123
						, ,	0∼75	510m ≦R ≦910m (E24 series)												
New/						D (±0.5%)	0~250	47m≦R<150m (E24 series)												
MCR50L	5025	2010	2	70	125	F (±1%)	0~200	150m ≤R < 300m (E24 series)	-55 ∼ +155	Yes										
						J(±5%)	0~150	300m ≤ R ≤ 910m (E24 series)												
							0~300	47m ≦R < 75m (E24 series)												
New/ MCR100L	6432	2512	3	70	125	F(±1%)	0~250	75m≦R<200m (E24 series)	-55 ∼ +155	Yes										
WICKTOOL	0432	2512	3	70	125	J (±5%)	0~200	200m ≤R < 560m (E24 series)	-00 ∼ +100	res										
							0~150	560m≤R≤910m (E24 series)												

^{*} Design and specifications are subject to change without notice. Carefully check the specification sheet supplied with the product before using or ordering it.

Part number description

MCR 10L **EQP** F **R100**

Part No.
MCR
General Purpose
Chip Resistors

Size	(mm) [inch]
10L	(2012) [0805]
18L	(3216) [1206]
25L	(3225) [1210]
50L	(5025) [2010]
1001	(6432) [2512]

	Type code										
Part No.	Code	Packaging specifications	Quantity / Reel								
MCR10L	EQP	Paper tape (4mm Pitch)	5,000								
MCR18L	EQP	Paper tape (4mm Pitch)	5,000								
MCR25L	JQP	Embossed tape (4mm Pitch)	4,000								
MCR50L JQP		Embossed tape (4mm Pitch)	4,000								
MCR100L	JQP	Embossed tape (4mm Pitch)	4,000								


Resistance tolerance	S	pecial part code
D (±0.5%) F (±1%)	S	47 ~ 91mΩ
J (±5%)	L	100∼910mΩ

Nominal resistance											
Resistance code, 3 or 4 digits.											
	Resistance Resistance										
	tolerance		code								
	FL,FS,JS	:	4 digits								
	JL	:	3 digits								
l '				•							

^{*} Rated voltage is determined from the following.

^{*} Rated voltage = \sqrt{Rated power × Resistance}

● Chip resistor dimensions and markings




<Marking method>
No marking

(Unit: mm)

Part No.	Type code	(mm)	(inch)	L	W	t	а	b	
MCR10L	EQP	2012	0805	2.00±0.10	1.25±0.10	0.55±0.10	0.60±0.20 ^{*1}	0.40±0.20	
							0.45±0.20 ^{*2}		
MCR18L	EQP	3216	1206	1206 3.20+0.15 -0.20 1.60±0.15		0.55±0.10	0.90±0.20 ^{*1}	0.50±0.25	
WORTOL	LGI	0210	1200			0.0010.10	0.75±0.20 ^{*2}	0.00±0.20	
MCR25L	10D	3225	1210	3.20+0.15	2.50±0.15	0.60±0.10	0.70±0.15	0.55±0.15	
MCR25L	JQP	3225	1210	-0.20	2.50±0.15	0.00±0.10	0.70±0.15	0.00±0.10	
MCR50L	JQP	5025	2010	5.00±0.15	2.50±0.15	0.60±0.10	0.55±0.15	0.70±0.15	
MCR100L	JQP	6432	2512	6.40+0.10	3.20+0.10	0.60±0.10	0.70±0.25	1.45±0.25	
TORTOOL	37	0.52	2312	-0.15	-0.15				

^{*1} Resistance range:47m Ω \sim 110m Ω

● Land pattern example



(Unit: mm)

2/5

Dimensions Part No.	Α	В	С	D
MCR10L	1.20	2.60	1.15	0.70
MCR18L	2.20	4.00	1.50	0.90
MCR25L	2.20	4.00	2.50	0.90
MCR50L	3.80	6.00	2.50	1.10
MCR100L	3.30	8.10	3.30	2.40



^{*2} Resistance range:120m $\Omega{\sim}910m\Omega$

Derating curve

■MCR10L/18L/25L/50L/100L

For resistors operated at the ambient temperature in excess 70°C, the load shall be derated in accordance with Fig.1.

■MCR25L/50L/100L

For resistors operated at the ambient temperature in excess 70°C or terminal temperature^{*4} in excess the rated terminal temperature, load shall be derated in accordance with Fig.1 and Fig.2.

*4: The measurement part of terminal temperature is center of fillet's surface with load.

Fig.1< Ambient temperature>





Fig.2< Terminal temperature>



Characteristics


Test items	Guaranteed value	Test conditions
Resistance	See P.1	20°C
		Measuring method : Measure Bottom
		terminal by 4 probes.
		Bottom terminal
		Probe
Variation of resistance	See P.1	Test temperature : +25/-55, +25/+155°C
w ith temperature		
Overload	±2.0%	Rated voltage(current)×2.5, 2s (MCR10L/18L)
		Rated voltage(current)×2.5, 5s (MCR25L/50L/100L)
Solderability	A new uniform coating of minimum of 95%	Rosin-ethanol solution (25% mass)
·	of the surface being immersed and	Soldering condition : 245±5°C
	no soldering damage.	Duration of immersion : 2.0±0.5s
Resistance to soldering	±1.0%	Soldering condition : 260±5°C
heat	No remarkable abnormality on the appearance.	Duration of immersion: 10±1s
Rapid change of temperature	±1.0%	Test temp.: -55°C~+125°C 1,000cycles (MCR10L/18L/25L/50L)
		750cycles (MCR100L)
		-55°C~ +155°C 750cycles (MCR25L)
		500cycles (MCR50L)
		250cycles (MCR100L)
Temperature	±3.0%	85°C, 85% (Relative humidity)
humidity storage		Test time: 1,000h
Endurance at 70°C	±3.0% (MCR10L/18L)	Ambient temperature : Ta=70°C (MCR10L/18L/25L/50L/100L)
	±1.0% (MCR25L/50L/100L)	Terminal temperature: Tk=125°C (MCR25L/50L/100L)
		Rated voltage(current): 1.5h:ON – 0.5h:OFF
		Test time: 1,000h
Endurance	±3.0% (MCR10L/18L)	Test temp.: 155°C
	±1.0% (MCR25L/50L/100L)	Test time: 1,000h
Resistance to solvent	±1.0%	23±5°C, Immersion cleaning, 5±0.5min
		Solvent : 2-propanol
Bend strength of	±1.0%	Endurance w ith 90mm w idth
the end face plating	Without mechanical damage such as breaks.	Deflection: 3mm (MCR10L/18L)
-	-	1mm (MCR25L/50L/100L)

Compliance Standard(s) : IEC 60115-1 / IEC 60115-8 JIS C 5201-1 / JIS C 5201-8



● Tape dimensions


■Paper tape



(Unit: mm)

Part No.	Type code	W	F	E	A0	В0	D0	P0	P1	P2	T2
MCR10L	EQP	8.0±0.3	3.5±0.05	1.75±0.1	1.65+0.2 -0.1	2.4+0.2 -0.1	Ф1.5+0.1 0	4.0±0.1	4.0±0.1	2.0±0.05	MAX1.1
MCR18L	EQP	8.0±0.3	3.5±0.05	1.75±0.1	1.95+0.1 -0.05	3.5+0.15 -0.05	Ф1.5+0.1 0	4.0±0.1	4.0±0.1	2.0±0.05	MAX1.1

■Embossed tape



(Unit: mm)

Part No.	Type code	W	F	E	A0	В0	D0	P0	P1	P2	K
MCR25L	JQP	8.0±0.2	3.5±0.05	1.75±0.1	3.0±0.1	3.5±0.1	Ф1.5+0.1 0	4.0±0.1	4.0±0.1	2.0±0.05	MAX1.1
MCR50L	JQP	12.0±0.2	5.5±0.05	1.75±0.1	2.9±0.1	5.3±0.1	Ф1.5+0.1 0	4.0±0.1	4.0±0.1	2.0±0.05	MAX1.1
MCR100L	JQP	12.0±0.2	5.5±0.05	1.75±0.1	3.4±0.1	6.6±0.1	Ф1.5+0.1 0	4.0±0.1	4.0±0.1	2.0±0.05	MAX1.1





Reel dimensions

Using two kinds of reels for taping.

■ MCR10L/18L/25L

■ MCR50L/100L





(Unit: mm)

Part No.	Α	В	С	D		
MCR10L						
MCR18L			9 +1.0 0			
MCR25L	Ф180 0 -1.5	Ф60 +1.0 0		Ф13±0.2		
MCR50L			13 +1.0			
MCR100L			0			

Notice

Precaution on using ROHM Products

1. If you intend to use our Products in devices requiring extremely high reliability (such as medical equipment (Note 1), aircraft/spacecraft, nuclear power controllers, etc.) and whose malfunction or failure may cause loss of human life, bodily injury or serious damage to property ("Specific Applications"), please consult with the ROHM sales representative in advance. Unless otherwise agreed in writing by ROHM in advance, ROHM shall not be in any way responsible or liable for any damages, expenses or losses incurred by you or third parties arising from the use of any ROHM's Products for Specific Applications.

(Note1) Medical Equipment Classification of the Specific Applications

recent medical Equipment Glacemedian of the opening applications			
JAPAN	USA	EU	CHINA
CLASSⅢ	CLASSII	CLASS II b	CLASSIII
CLASSIV		CLASSⅢ	

- 2. ROHM designs and manufactures its Products subject to strict quality control system. However, semiconductor products can fail or malfunction at a certain rate. Please be sure to implement, at your own responsibilities, adequate safety measures including but not limited to fail-safe design against the physical injury, damage to any property, which a failure or malfunction of our Products may cause. The following are examples of safety measures:
 - [a] Installation of protection circuits or other protective devices to improve system safety
 - [b] Installation of redundant circuits to reduce the impact of single or multiple circuit failure
- 3. Our Products are not designed under any special or extraordinary environments or conditions, as exemplified below. Accordingly, ROHM shall not be in any way responsible or liable for any damages, expenses or losses arising from the use of any ROHM's Products under any special or extraordinary environments or conditions. If you intend to use our Products under any special or extraordinary environments or conditions (as exemplified below), your independent verification and confirmation of product performance, reliability, etc, prior to use, must be necessary:
 - [a] Use of our Products in any types of liquid, including water, oils, chemicals, and organic solvents
 - [b] Use of our Products outdoors or in places where the Products are exposed to direct sunlight or dust
 - [c] Use of our Products in places where the Products are exposed to sea wind or corrosive gases, including Cl₂, H₂S, NH₃, SO₂, and NO₂
 - [d] Use of our Products in places where the Products are exposed to static electricity or electromagnetic waves
 - [e] Use of our Products in proximity to heat-producing components, plastic cords, or other flammable items
 - [f] Sealing or coating our Products with resin or other coating materials
 - [g] Use of our Products without cleaning residue of flux (Exclude cases where no-clean type fluxes is used. However, recommend sufficiently about the residue.); or Washing our Products by using water or water-soluble cleaning agents for cleaning residue after soldering
 - [h] Use of the Products in places subject to dew condensation
- 4. The Products are not subject to radiation-proof design.
- 5. Please verify and confirm characteristics of the final or mounted products in using the Products.
- 6. In particular, if a transient load (a large amount of load applied in a short period of time, such as pulse, is applied, confirmation of performance characteristics after on-board mounting is strongly recommended. Avoid applying power exceeding normal rated power; exceeding the power rating under steady-state loading condition may negatively affect product performance and reliability.
- 7. De-rate Power Dissipation depending on ambient temperature. When used in sealed area, confirm that it is the use in the range that does not exceed the maximum junction temperature.
- 8. Confirm that operation temperature is within the specified range described in the product specification.
- 9. ROHM shall not be in any way responsible or liable for failure induced under deviant condition from what is defined in this document.

Precaution for Mounting / Circuit board design

- 1. When a highly active halogenous (chlorine, bromine, etc.) flux is used, the residue of flux may negatively affect product performance and reliability.
- 2. In principle, the reflow soldering method must be used on a surface-mount products, the flow soldering method must be used on a through hole mount products. If the flow soldering method is preferred on a surface-mount products, please consult with the ROHM representative in advance.

For details, please refer to ROHM Mounting specification

Precautions Regarding Application Examples and External Circuits

- 1. If change is made to the constant of an external circuit, please allow a sufficient margin considering variations of the characteristics of the Products and external components, including transient characteristics, as well as static characteristics.
- 2. You agree that application notes, reference designs, and associated data and information contained in this document are presented only as guidance for Products use. Therefore, in case you use such information, you are solely responsible for it and you must exercise your own independent verification and judgment in the use of such information contained in this document. ROHM shall not be in any way responsible or liable for any damages, expenses or losses incurred by you or third parties arising from the use of such information.

Precaution for Electrostatic

This Product is electrostatic sensitive product, which may be damaged due to electrostatic discharge. Please take proper caution in your manufacturing process and storage so that voltage exceeding the Products maximum rating will not be applied to Products. Please take special care under dry condition (e.g. Grounding of human body / equipment / solder iron, isolation from charged objects, setting of lonizer, friction prevention and temperature / humidity control).

Precaution for Storage / Transportation

- 1. Product performance and soldered connections may deteriorate if the Products are stored in the places where:
 - [a] the Products are exposed to sea winds or corrosive gases, including Cl₂, H₂S, NH₃, SO₂, and NO₂
 - [b] the temperature or humidity exceeds those recommended by ROHM
 - [c] the Products are exposed to direct sunshine or condensation
 - [d] the Products are exposed to high Electrostatic
- Even under ROHM recommended storage condition, solderability of products out of recommended storage time period
 may be degraded. It is strongly recommended to confirm solderability before using Products of which storage time is
 exceeding the recommended storage time period.
- 3. Store / transport cartons in the correct direction, which is indicated on a carton with a symbol. Otherwise bent leads may occur due to excessive stress applied when dropping of a carton.
- 4. Use Products within the specified time after opening a humidity barrier bag. Baking is required before using Products of which storage time is exceeding the recommended storage time period.

Precaution for Product Label

A two-dimensional barcode printed on ROHM Products label is for ROHM's internal use only.

Precaution for Disposition

When disposing Products please dispose them properly using an authorized industry waste company.

Precaution for Foreign Exchange and Foreign Trade act

Since concerned goods might be fallen under listed items of export control prescribed by Foreign exchange and Foreign trade act, please consult with ROHM in case of export.

Precaution Regarding Intellectual Property Rights

- 1. All information and data including but not limited to application example contained in this document is for reference only. ROHM does not warrant that foregoing information or data will not infringe any intellectual property rights or any other rights of any third party regarding such information or data.
- 2. ROHM shall not have any obligations where the claims, actions or demands arising from the combination of the Products with other articles such as components, circuits, systems or external equipment (including software).
- 3. No license, expressly or implied, is granted hereby under any intellectual property rights or other rights of ROHM or any third parties with respect to the Products or the information contained in this document. Provided, however, that ROHM will not assert its intellectual property rights or other rights against you or your customers to the extent necessary to manufacture or sell products containing the Products, subject to the terms and conditions herein.

Other Precaution

- 1. This document may not be reprinted or reproduced, in whole or in part, without prior written consent of ROHM.
- 2. The Products may not be disassembled, converted, modified, reproduced or otherwise changed without prior written consent of ROHM.
- In no event shall you use in any way whatsoever the Products and the related technical information contained in the Products or this document for any military purposes, including but not limited to, the development of mass-destruction weapons.
- 4. The proper names of companies or products described in this document are trademarks or registered trademarks of ROHM, its affiliated companies or third parties.

Notice-PAA-E Rev.004

General Precaution

- 1. Before you use our Products, you are requested to carefully read this document and fully understand its contents. ROHM shall not be in any way responsible or liable for failure, malfunction or accident arising from the use of any ROHM's Products against warning, caution or note contained in this document.
- 2. All information contained in this document is current as of the issuing date and subject to change without any prior notice. Before purchasing or using ROHM's Products, please confirm the latest information with a ROHM sales representative.
- 3. The information contained in this document is provided on an "as is" basis and ROHM does not warrant that all information contained in this document is accurate and/or error-free. ROHM shall not be in any way responsible or liable for any damages, expenses or losses incurred by you or third parties resulting from inaccuracy or errors of or concerning such information.

Notice – WE Rev.001